

KOHLER®

SDMO®



HX 6000 C5

PORTABLE POWER

GENERATING SET Range INTENS

PRODUCT ADVANTAGES

- Solid and high-performance equipment
- Generating set guaranteed 3 years
- HONDA Professional Engine

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 6000 C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	5,60
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	6,10
75% cons. (l/h) *	2,50
75% Autonomy (h) *	2,40
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	83
Acoustic pressure level @7m in dB(A)	69

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX390_C5
Engine Type	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	389
Oil system capacity including filters (l)	1,10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	77
Width (cm)	57
Height (cm)	59
Dry Weight (kg)	79

PACKAGING

Packaging type	Box
Length (cm)	78,50
Width (cm)	58
Height (cm)	59,50
Weight (kg)	81,50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	192
weight of the packaged Pallet (kg)	499

KOHLER®
SDMO®

27/05/2022

HX 6000 C5 - PORTABLE POWER - GENERATING SET INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

KOHLER®

SDMO®

HX 6000 C5

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R02

This set includes the hour meter and the differential circuit breaker.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB2

Trolley kit for the generating sets superior to 6kW



R19

Maintenance kit for Honda GX390 engines (except Alizé 6000E and Alizé 7500 TE)



RH1

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V

KOHLER®

SDMO®

27/05/2022

HX 6000 C5 - PORTABLE POWER - GENERATING SET INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervem - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com